

LV3-8 for imc CRONOScompact

8-channel Differential Amplifier

The LV3-8 is a differential measurement amplifier with 8 channels for measuring:

- Voltage and current (20 mA)
- IEPE/ICP sensors (with optional DSUB-15 plug)

Highlights

- Economical, high-resolution measuring of current and voltage
- Finely adjustable input voltage range ($\pm 5\text{ mV}$ to $\pm 50\text{ V}$)
- High signal bandwidth up to 48 kHz
- Each channel with its own adjustable filter (e.g., anti-aliasing filter) and simultaneous A/D converter
- Supports imc Plug & Measure (Transducer Electronic Data Sheets)



CRC/LV3-8

Typical applications

- Ideally suited for measurements of signals, voltage-based sensors as well as 20 mA process variables with higher bandwidths.

imc CRONOScompact - modular measurement system

imc CRONOScompact is a modular and reconfigurable hardware a "rack"-based series of devices available in a variety of housing sizes and device frames. imc CRONOScompact (CRC) plug-in-modules can be inserted into the system (CRC-400GP).

Once the modules are plugged into a portable or rack-based housing, they are electrically connected to the CRC-system and are supplied by the system with power. The data storage will be managed by the CRC-system.

Rack-based modules ("-R") differ from the standard modules only in terms of the front panel's attachment mechanism.



imc CRONOScompact plug-in-modules



imc CRONOScompact portable housing

Overview of available variants

Standard version		ET Version *	
Order Code:	article no.	article no.	Remarks
CRC/LV3-8	11700015	11710014	for imc CRONOScompact
CRC/LV3-8-R	11700105	11710064	for imc CRONOScompact RACK
CRC/LV3-8-L	11700223	117100xx	variant with LEMO sockets
CRC/LV3-8-L-R	11700224		variant with LEMO sockets for the 19"RACK

* ET: Version in extended temperature range

Standard version		ET-Version	
Order Code:	article no.	article no.	Remarks
CRC/LV3-8-SUPPLY-L	11700225		with integrated sensor supply
CRC/LV3-8-SUPPLY-L-R	11700226		with integrated sensor supply for 19"RACK

Included accessories

DSUB-15 plug for the module variant with DSUB-15 input connectors		article no.
2x ACC/DSUBM-U4	DSUB-15 plug with screw terminals for 4-channel voltage measurement	13500166
Documents		
Getting started with imc CRONOScompact (one copy per delivery / system)		
Device certificate		

Optional accessories

Documents		
SERV/CAL-PROT	Calibration protocol per amplifier imc manufacturer calibration certificate with measurement values and list of calibration equipment used (pdf).	150000566
SERV/CAL-PROT-PAPER	Calibration protocol per amplifier (paper print) imc manufacturer calibration certificate with measurement values and list of calibration equipment used with signature and seal.	150000578
Device certificates and calibration protocols: Detailed information on certificates supplied, the specific contents, underlying standards (e.g. ISO 9001 / ISO 17025) and available media (pdf etc.) can be found on our website, or you can contact us directly.		

DSUB-15 plugs

- | | | |
|-----------------------|----------------------------------------------------------------------------------------------------------------------------------|----------|
| • ACC/DSUBM-TEDS-U4 | DSUB-15 plug with screw terminals for 4-channel voltage measurement | 13500189 |
| • ACC/DSUBM-I4 | DSUB-15 plug with screw terminals for 4-channel current measurement of up to 50 mA (50 Ω shunt, scaling factor: 0.02 A/V) | 13500168 |
| • ACC/DSUBM-TEDS-I4 | version with TEDS support, according to IEEE 1451 for use with imc Plug & Measure | 13500192 |
| • ACC/DSUB-ICP4-METAL | DSUB-15 plug with screw terminals for conditioning of 4 IEPE/ICP inputs | 13500471 |

Mounting brackets for fixed installations of imc CRONOScompact devices (CRC)

- | | | |
|--------------------|-------------------------------|----------|
| • CRC/BRACKET-CON | mounting bracket 90° | 11700153 |
| • CRC/BRACKET-90 | mounting bracket for DIN-Rail | 11700152 |
| • CRC/BRACKET-BACK | mounting bracket for DIN-Rail | 11700154 |

Technical Specs - CRC/LV3-8

Inputs, measurement modes, terminal connection			
Parameter	Value		Remarks
Inputs	8		
Measurement modes DSUB	voltage measurement current measurement current feed sensors		shunt plug (ACC/DSUBM-I4) with DSUB-15 expansion plug: ACC/DSUB-ICP4-METAL, not isolated ACC/DSUBM-ICP2I-BNC-S/-F ¹ , isolated
Measurement modes LEMO	voltage measurement current measurement		with external shunt
Terminal connection Standard LEMO	2x DSUB-15 8x LEMO.1B.307		4 channels per plug 1 channel per plug
Sampling rate, Bandwidth, Filter, TEDS			
Parameter	Value typ.	min. / max.	Remarks
Sampling rate	≤100 kHz		per channel
Bandwidth	0 Hz to 48 kHz 0 Hz to 30 kHz		-3 dB -0.1 dB
Max. Signal Slew-Rate	1.2 V/μs		
Filter (digital) cut-off frequency characteristic order	10 Hz to 20 kHz		Butterworth, Bessel low pass or high pass filter: 8th order band pass: LP 4th and HP 4th order Anti-aliasing filter: Cauer 8.order with $f_{\text{cutoff}} = 0.4 f_s$
Resolution	16 Bit		internal processing 24 Bit
TEDS	conforming to IEEE 1451.4 Class II MMI		esp. with ACC/DSUBM-TEDS-xx (DS2433) not supported: DS2431 (typ. IEPE/ICP sensor)

- 1 When using the two-channel IEPE plug in combination with the analog inputs, which provide four channels per socket, only channels 1 and 3 can be used.

General			
Parameter	Value typ.	min. / max.	Remarks
Overvoltage protection		$\pm 80\text{ V}$ $\pm 50\text{ V}$	permanent, differential input range $>\pm 10\text{ V}$ or device switched off input range $\leq \pm 10\text{ V}$
Input coupling	DC		
Input configuration	differential		
Input impedance	1 M Ω 20 M Ω		range $>\pm 10\text{ V}$ range $\leq \pm 10\text{ V}$
Auxiliary supply			for IEPE/ICP expansion plug
voltage	+5 V	$\pm 5\%$	independent of optional
available current	$>0.26\text{ A}$	$>0.2\text{ A}$	sensor supply, short circuit proof
internal resistance	1.0 Ω	$<1.2\text{ }\Omega$	power per DSUB-plug
Voltage measurement			
Parameter	Value typ.	min. / max.	Remarks
Input ranges	$\pm 50\text{ V}$, $\pm 25\text{ V}$, $\pm 10\text{ V}$, $\pm 5\text{ V}$, $\pm 2.5\text{ V}$, $\pm 1\text{ V}$... $\pm 5\text{ mV}$		
Maximum input voltage		-11 V to +15 V	between $\pm\text{IN}$ and CHASSIS; input range $\leq \pm 10\text{ V}$
Gain error	0.02 %	0.05 %	of the reading
Gain drift	10 ppm/K $\cdot\Delta T_a$	30 ppm/K $\cdot\Delta T_a$	$\Delta T_a = T_a - 25\text{ }^\circ\text{C} $; T_a = ambient temperature
Offset error	0.02 %	$\leq 0.05\%$ $\leq 0.06\%$ $\leq 0.15\%$	of the range, at 25 $^\circ\text{C}$ $>\pm 50\text{ mV}$ $\leq \pm 50\text{ mV}$ $\leq \pm 10\text{ mV}$
Offset drift	$\pm 40\text{ }\mu\text{V/K}\cdot\Delta T_a$ $\pm 0.7\text{ }\mu\text{V/K}\cdot\Delta T_a$ $\pm 0.1\text{ }\mu\text{V/K}\cdot\Delta T_a$	$\pm 200\text{ }\mu\text{V/K}\cdot\Delta T_a$ $\pm 6\text{ }\mu\text{V/K}\cdot\Delta T_a$ $\pm 1.1\text{ }\mu\text{V/K}\cdot\Delta T_a$	range $>\pm 10\text{ V}$ range $\pm 10\text{ V}$ to $\pm 0.25\text{ V}$ range $\leq \pm 0.1\text{ V}$ $\Delta T_a = T_a - 25\text{ }^\circ\text{C} $; T_a = ambient temperature
Nonlinearity	30 ppm	$\leq 90\text{ ppm}$	
Common mode rejection ranges	$\pm 50\text{ V}$ to $\pm 25\text{ V}$ $\pm 10\text{ V}$ to $\pm 50\text{ mV}$ $\pm 20\text{ mV}$ to $\pm 5\text{ mV}$	$>70\text{ dB}$ $>90\text{ dB}$ $>132\text{ dB}$	Common mode voltage (DC..60 Hz): $\pm 50\text{ V}$ $\pm 10\text{ V}$ $\pm 10\text{ V}$
Noise	3.6 μV_{rms} 0.6 μV_{rms} 0.14 μV_{rms}	5.5 μV_{rms} 1.0 μV_{rms} 0.26 μV_{rms}	bandwidth 0.1 Hz to 50 kHz 0.1 Hz to 1 kHz 0.1 Hz to 10 Hz

Current measurement with shunt plug			
Parameter	Value typ.	min. / max.	Remarks
Input ranges	±50 mA, ±20 mA, ±10 mA, ±5 mA, ±2 mA, ±100 µA1 mA		50 Ω shunt in terminal plug
Shunt impedance	50 Ω		external plug ACC/DSUBM-I4
Over load protection		±60 mA	permanent
Maximum input voltage		-11 V to +15 V	between ±IN and CHASSIS
Input configuration	differential		50 Ω shunt in terminal plug
Gain error	0.02 %	≤0.06 % ≤0.1 %	of reading plus error of 50 Ω shunt
Gain drift	+15 ppm/K·ΔT _a	+55 ppm/K·ΔT _a	ΔT _a = T _a -25 °C ; T _a = ambient temperature
Offset error	0.02 %	≤0.05 %	of the range
Current noise	40 nA _{rms} 0.7 nA _{rms} 0.17 nA _{rms}	70 nA _{rms} 12 nA _{rms} 0.3 nA _{rms}	Bandwidth: 0.1 Hz to 50 kHz 0.1 Hz to 1 kHz 0.1 Hz to 10 Hz

Sensor supply module (LV3-8-SUPPLY, LV3-8-L-SUPPLY)				
Parameter	Value typ.		max.	Remarks
Configuration options	5 selectable settings			The sensor supply module always has 5 selectable voltage settings. default selection: +5 V to +24 V
Output voltage	Voltage (+2.5 V) +5.0 V +10 V +12 V +15 V +24 V (±15 V)	Current 580 mA 580 mA 300 mA 250 mA 200 mA 120 mA 190 mA	Netpower 1.5 W 2.9 W 3.0 W 3.0 W 3.0 W 2.9 W 3.0 W	set jointly for all eight channels optional, special order, +12 V or 15 V can be replaced by +2.5 V preferred selection with 2.5 V: +2.5 V, +5.0 V, +10 V, +12 V, +24 V optional, special order: +15 V can be replaced by ±15 V
Isolation Standard: option, upon request:	non isolated isolated			output to case (CHASSIS) nominal rating: 50V, test voltage (10sec.): 300 V, not available with option ±15 V.
Short-circuit protection	unlimited duration			to output voltage reference ground
Accuracy of output voltage	<0.25 % 0.5 % 0.9 % 1.5 %			at terminals, no load at 25°C over entire temperature range plus with optional bipolar output voltage
Max. capacitive load	>4000 µF >1000 µF >300 µF			2.5 V to 10 V 12 V, 15 V 24 V



An Axiometrix Solutions Brand

Contact imc

Address

imc Test & Measurement GmbH
Voltastr. 5
13355 Berlin

Phone: (Germany): +49 30 467090-0

E-Mail: info@imc-tm.de

Internet: <https://www.imc-tm.com>

Tech support

If you have problems or questions, please contact our tech support:

Phone: (Germany): +49 30 467090-26

E-Mail: hotline@imc-tm.de

Internet: <https://www.imc-tm.com/service-training/>

Service and maintenance

Our service team is at your disposal for service and maintenance inquiries:

Phone: (Germany): +49 30 629396-333

E-Mail: imc-service@axiometrixsolutions.com

Internet: <https://www.imc-tm.com/service>

imc ACADEMY - Training center

The safe handling of measurement devices requires a good knowledge of the system. At our training center, experienced specialists are here to share their knowledge.

E-Mail: schulung@imc-tm.de

Internet: <https://www.imc-tm.com/service-training/imc-academy>

International partners

You will find the contact person responsible for you in our overview list of imc partners:

Internet: <https://www.imc-tm.com/imc-worldwide/>

imc @ Social Media

<https://www.facebook.com/imcTestMeasurement>

<https://www.youtube.com/c/imcTestMeasurementGmbH>

https://x.com/imc_de

<https://www.linkedin.com/company/imc-test-&-measurement-gmbh>